



www.idx.tv

Specifications

- DC output : 2 channels (4 pin XLR connector, No.1 minus, No. 4 plus)
- Output Voltage : Voltage of ENDURA batteries(14.4V)
- Discharge current : Maximum 10A per channel
- Number of batteries to be used : Maximum 8 x of E-50 (PowerLinked)
- LED display : Output voltage 14V or higher Green LED on
: Output voltage below 14V Red LED on
: Output voltage 12V or below LED off (power off)
- Dimensions : 80(W)x165(H)x217(D)mm(128(W)mm (feet extended)
- Weight : Approx. 1.3Kgs

Applicable batteries

E-50, E-50S, E-80S & E-80

Caution

Maximum discharge current when using 2 x E-50 or E-50S is 8A (maximum 4A per one ENDURA E-50 or one E-50S). Loads over 8A may activate the battery protection circuit and automatically stop the supply of power.

Maximum discharge current when using 2 x E-80 or E-80S is 12A (maximum 6A per one ENDURA E-80 or one E-80S). Loads over 12A may activate the battery protection circuit and automatically stop the supply of power.

In Japan/Asia

IDX COMPANY LTD.
6-28-11 Shukugawara,
Tama-ku, Kawasaki-Shi,
Kanagawa-ken 214-0021,
Japan

Sales and service

Phone +81-44-850-8801
Fax +81-44-850-8838
E-mail idxjapan@idx.tv

In the United States

IDX System Technology
1602 Lockness Place,
Torrance, CA 90501 USA

Sales and Service

Phone +1-310-891-2800
Fax +1-310-891-3600

E-mail idxusa@idx.tv

In Europe/Middle East

IDX Technology Europe Ltd.
Unit 34 Metropolitan Centre,
3 Taunton Road, Greenford,
Middlesex UB6 8UQ, England

Sales and service

Phone +44-20-8813-1666
Fax +44-20-8813-1777

E-mail idxeurope@idx.tv